

How LEDs cope with overvoltage

www.lec-expert.com

[Read this article on the website \(URL\)](#)



Overvoltage poses a direct threat to the integrity and longevity of outdoor LED lighting. LEC has the solution.

All lighting systems with electronic components are vulnerable to overvoltage, especially LED luminaires. The use of adequate protection is thus vital to ensure their **long-term durability**.


Risks of overvoltage and safety recommendations for LED luminaires

LEC's experts prioritise **safety** and **longevity** in their lighting systems, and thus follow the recommendations provided by the [French Lighting Union's joint statement](#), which precisely addresses the **various causes of overvoltage** for outdoor luminaires.

A - Transient overvoltage caused by lightning

There are two important factors to consider when protecting against lightning:

1. The lightning density (measured in Ng), which is the number of lightning impacts per km² and per year in an area
2. The Keraunic level (measured in Nk), which is the number of days in a year when thunder can be heard



Risk of overvoltage across France, based on their Nk (Ng = Nk/10)

The **NF-C-15-100** and the **UTE C 15-443 risk guide** set out regulations to minimise transient overvoltage and the risk of malfunction, including **cascade protection** with several types of surge arresters installed throughout the installation:

- **Type 1 surge protector:** effective against high-energy waves, at the top of the installation where there is a significant risk of a lightning strike e.g. when located close to a lightning rod.
- **Type 2 surge protector:** at the top of the installation, in parallel with the low-voltage main distribution panel, or near to vulnerable equipment.
- **Type 2 or 3 surge protector:** close to (a dozen metres) particularly vulnerable equipment or spread-out installations.

N.B: it is recommended to fit type 2 or 3 surge protectors at the base of **pole floodlights**. While these protectors may not be able to withstand as much overvoltage as type 1, their selectivity makes for good long-term protection.

Cascade protection is vital as it allows for:

Published on 30 March 2017

Categories:

Norms & Quality - Solutions by LEC

Tags:

LED luminaire - lightning - outdoor lighting - overvoltage - surge protector

PDF generated on 13 July 2025

www.lec-lyon.com

How LEDs cope with overvoltage

- **Surge protectors** to be calibrated according to overvoltage **waves**: the most powerful receive the stronger waves first and filter them.
- **Easy replacement** of the protectors, which can withstand a specific amount and level of strikes.
- Overvoltage **wave reamplification** to be taken into account e.g. an overvoltage cut at 1.5 kV may reamplify itself at 3kV thirty metres down the line.

Here is the [Citadel of Bonifacio](#) illuminated with 78 of LEC's [4660-Corsica projectors](#). They are all equipped with surge protection cascaded in terms of position and features, using type 1, 2 and 3 equipment.



In July 2015, the Bonifacio Citadel was fitted with luminaires by LEC to provide its thousands of visitors with a spectacular night-time view.

B - Commutating overvoltage

This occurs when outdoor LED lighting installation is **turned on as usual** or when a **neighbouring installation** is switched on. It affects power equipment, LED modules and built-in control systems.

A **2 kV protection** is recommended to ensure LED luminaires are fully safeguarded. The surge protectors used against lightning also provide decent protection against commutating overvoltage, as do type 2 and 3 protectors, which are perfectly appropriate to filter such overvoltage.

C - TOV (Temporary Over Voltage)

This occurs when a neutral **conductor is disconnected** within a **three-phase** power supply.

To mitigate this risk, the **electrical cabinet should be protected**, and the networks should undergo **regular maintenance**.

LEC's solutions to minimising the risk of overvoltage to outdoor lighting

Nowadays, the **risk of overvoltage is constantly on the rise** as the number of devices vulnerable to this problem multiplies, and networks become more polluted with the increased use of electronics. LEC works hard at every stage of the product lifestyle (design, manufacturing and installation) to ensure its outdoor LED luminaires are up to the job. This includes:

- Conducting several surge protector **development tests** in the laboratory
- Educating **fitters** on the risks of overvoltage
- Allowing for overvoltages bigger than the local keraunic guidelines, to ensure proper operation **in all conditions** and all over the world

How LEDs cope with overvoltage

- The **systematic protection** using surge protectors, even in statistically low-risk areas as defined by the UTE –C 15-443
- The installation of **230 V floodlights certified** for overvoltage levels of **up to 10 kV**, to guarantee complete resistance when line protections are limited in virtue of the distance to type 2 and 3 surge protectors fitted upstream (ground-recessed or scattered luminaires)
- Protection of 230 V inputs, as well as **dimming inputs** such as 0-10V, DMX, DALI, which can all encounter overvoltage
- The all-in-one solution of **surge protectors** fitted throughout the installation for reliable and easy-to-maintain cascade protection

All these measures are taken to guarantee that our products are durable and safe, satisfying the needs of **city lighting master plans** and **light designers' artistic projects**

Do you have a LED outdoor lighting project in an overvoltage high-risk area? Ask for [advice from a LEC expert](#).